

PA2 KIT

Quick Installation Guide



Suitable for PA2-KIT series products

Fanvil Technology Co., Ltd

Website: www.fanvil.com

E-Mail: sales@fanvil.com support@fanvil.com

Tel: +86-755-2640-2199 Fax: +86-755-2640-2618

Add: 10/F Block A, Dualshine Global Science Innovation Center,
Honglang North 2nd Road, Bao'an District, Shenzhen, China

A.Module Features

	<p>Speaker module</p> <p>5W/8Ω Waterproof loudspeaker, The diameter of the horn is 57mm, and 13.7mm high. With 150cm Shielding wire.</p>
	<p>Camera module</p> <p>1.0M 1/4" H62 CMOS sensor, color .1Lux@F1.2,black/white 0.01Lux@F1.2.H.264,support dual stream; 0.1M~6Mbps variable; 1~30f/s variable. Main stream:1280*720;sub-stream: 704*576;</p>
	<p>Microphone Module</p> <p>Sensitivity -38dB±2, standard working voltage 3 v, the maximum working voltage 10 v, output impedance≤2.2KΩ, diameter of the microphone is 9.7mm and 4.7mm high. With 150cm Shielding wire.</p>
	<p>Button Module</p> <p>The diameter of the button is 16mm, and 23.8mm high, and the self-restorable stainless steel button. With 150cm Shielding wire.</p>

Fanvil Technology Co., Ltd

Website: www.fanvil.com
 EMail: sales@fanvil.com support@fanvil.com
 Tel: +86-755-2640-2199 Fax: +86-755-2640-2618
 Add: 10/F Block A, Dualshine Global Science Innovation Center,
 Honglang North 2nd Road, Bao'an District, Shenzhen, China

B.PA2 Connections




- ① SPK: Speaker connector;
- ② LED: status indicate of button
- ③ KEY: Connection of button
- ④ MIC: microphone connection
- ⑤ Camera: FANVIL IP camera connection. You can connect IP camera to PA2 with CAT5e cable


Fanvil Technology Co., Ltd

Website: www.fanvil.com
Email: sales@fanvil.com support@fanvil.com
Tel: +86-755-2640-2199 Fax: +86-755-2640-2618
Add: 10/F Block A, Dualshine Global Science Innovation Center,
Honglang North 2nd Road, Bao'an District, Shenzhen, China


C. Mounting Dimensions



Speaker module



IP camera module



Microphone module



Button module

- A: Attach the mounting dimensions diagram to the position where you want to install.
- B: To make some holes by the actual size.
- C: Tear off the two - sided adhesive film of the module and fix the module to the device.
- D: Fixed screw.
- E: Connect modules to PA2 Gateway by cable.

Note: The data scanned by the qr code is the Mac address and Auth code, which you only needs to enter the corresponding Auth code on web to Active PA2 to connect the camera module. You can use QR Reader APP to scan the QR code.



MAC=00:12:17:6b:b3:e9&Active
Code=d7a96b6ed619e2e7a0fec51ecb36bb0f

Fanvil Technology Co., Ltd

Website: www.fanvil.com
 Email: sales@fanvil.com support@fanvil.com
 Tel: +86-755-2640-2199 Fax: +86-755-2640-2618
 Add: 10/F Block A, Dualshine Global Science Innovation Center,
 Honglang North 2nd Road, Bao'an District, Shenzhen, China